

## IFP-300 / IFP-300B

### Intelligent Fire Alarm Control Panel

The IFP-300 (red) and IFP-300B (black) are intelligent analog/addressable fire alarm control panels (FACP) and are direct replacements for the IFP-100 FACP. The IFP-300 panel contains one built-in signaling line circuit (SLC), which can support 159 (IDP/SK) System Sensor® sensors and 159 IDP/SK modules or 127 (SD) Hochiki® devices per loop. Additional SLC loops can be added using the model 6815 SLC expander for SK/IDP devices to increase the overall point capacity to a maximum of 300 points per panel, or model 5815XL for SD devices to increase the overall point capacity to a maximum of 254 points per panel.

The IFP-300 has the interconnection capability for up to 32 panels. The system has two modes of operation, multiple panels covering one larger building, or multiple independent buildings. The SK-NIC Network Interface Card is used to network panels together. Copper wire or fiber optic cable panel connectivity can be used within the same networked system.

IFP-300 has a built-in dual phone line, digital alarm communicator/transmitter (DACT) with IP and optional cellular technologies, form-C trouble relay, and two programmable form-C relays. The IFP-300 has powerful features such as detector sensitivity, day/night thresholds, drift compensation, pre-trouble maintenance alert, and calibration trouble alert.

The IFP-300 supports a variety of devices, including RA-2000, RA-1000 or RA-100 remote annunciators, 5824 serial/parallel printer interface modules (for printing system reports), RPS-1000 power modules, and IDP, SK, or SD devices.



IFP-300B

## FEATURES & BENEFITS

- Network support for up to 32 Sites
- Built-in support for up to 159 IDP/SK detectors and 159 IDP/SK modules or 127 SD SLC devices
- Four line LCD display with 40 characters per line
- Available in a red or black cabinet
- Can be surface or flush mounted
- Built-in USB interface for convenient and quick programming
- Firmware can be upgraded in the field
- Network card allows copper network connection with a multi-mode or single-mode fiber connection option
- Built-in dual phone line, digital alarm communicator/transmitter (DACT) with IP and optional cellular technologies
- JumpStart® auto programming feature for easy programming
- Supports up to four SWIFT® wireless gateways. Each gateway can have up to 49 wireless devices
- Supports Class B (Style 4) and Class A (Style 6 or Style 7) configuration for SLC, and SBUS
- Built-in NAC synchronization for devices from AMSECO®, Gentex®, System Sensor®, and Wheelock®

# IFP-300 Technical Specifications

## PHYSICAL:

**Overall Dimensions:** 26.4"H x 16.4"W x 4.11"D

**Weight:** 45 lbs.

**Color:** Red or Black

## ENVIRONMENTAL

**Operating Temperature:** 32°F to 120°F (0°C to 49°C)

**Humidity:** 0 to 93% relative humidity (non-condensing)

## ELECTRICAL:

**IFP-300 Primary AC:** 120VAC @ 60 Hz, 3.3A Total Accessory Load: 6A @ 24VDC power-limited

**Standby Current:** 190mA

**Alarm Current:** 250mA

**Battery Charging Capacity:** 17 to 55AH

**Battery Size:** 18AH max. allowed in control panel cabinet. Larger capacity batteries can be housed in RBB accessory cabinet.

## AGENCY LISTINGS AND APPROVALS

**NFPA 13, NFPA 15, NFPA 16, NFPA 70, & NFPA**

**72:** Central Station; Remote Signaling; Local Protective Signaling Systems; Auxiliary Protected Premises Unit; & Water Deluge Releasing Service

**UL Listed:** S2766

**CSFM:** 7165-0559:0504

**FDNY:** COA#6245

**FM approved**

## APPROVED RELEASING SOLENOIDS

Asco T8210A107 24 VDC 3 A max 0 Hz

Asco 8210G207 24 VDC 3 A max 0 Hz

## COMPATIBLE DEVICES

See the data sheets listed below for a complete listing of the IDP, SK, SWIFT or SD devices.

**350361:** IDP Device Protocol data sheet **53623:**

SK Device Protocol data sheet **350360:** SD

Device Protocol data sheet **350615 & 350617:**

SWIFT devices data sheet

## ORDERING INFORMATION

**IFP-300:** Intelligent Fire Alarm Control Panel. Red Cabinet.

**IFP-300B:** Intelligent Fire Alarm Control Panel Black Cabinet.

## SBUS ACCESSORIES

**RA-2000, RA-1000, RA-1000R, RA-100,**

**RA-2000GRAY:** Remote annunciators

**6815:** Signal Line Circuit (SLC) Expander for IDP or SK devices

**5815XL:** Signal Line Circuit (SLC) Expander for SD devices

**RPS-1000:** Power Supply

**5496:** NAC Expander

**5824:** Serial/Parallel Module

**5880:** LED I/O Module

**5865-3 or 5865-4:** LED Annunciator

**5883:** Relay Interface

## MISCELLANEOUS ACCESSORIES

**HFSS:** Software Suite. Provides programming, upload/download and event reporting

**RBB:** Remote Battery Box Cabinet. Use for backup batteries up to 35 AH. Dimensions: 16" W x 10" H x 6" D

**SK-SCK:** Seismic Compliance Kit

**SK-NIC:** Network Interface Card

**SK-NIC-KIT:** Installation Accessory Kit

**SK-FML:** Fiber-Optic Multi Mode, transmitter and receiver

**SK-FSL:** Fiber-Optic Single Mode

**CELL-MOD:** Cellular Communicator in Plastic Enclosure

**CELL-CAB-SK:** Cellular Communicator in Metal Enclosure with lock and key

Flexput®, JumpStart®, Honeywell®, System Sensor®, and SWIFT® are registered trademarks of, and Farenhyt™ is a trademark of Honeywell International, Inc.

Amseco® is a registered trademark of Potter Electric Signal Company, LLC. Gentex® is a registered trademark of Gentex Corporation. Hochiki® is a registered trademark of Hochiki Corporation. Wheelock® is a trademark of Cooper Technologies Company.

This document is not intended to be used for installation purposes. We try to keep our product information up-to date and accurate. We cannot cover all specific applications or anticipate all requirements. All specifications are subject to change without notice.

For Technical Support, Please call 800-446-6444.

## Honeywell Farenhyt

12 Clintonville Road  
Northford, CT 06472  
800-328-0103  
www.farenhyt.com